



2020 Baseline Wattages

The wattages below apply for T8 lamp replacement.

T8 Retrofit Baseline Wattage Figures

8-foot T8 Lamps

Fixture	Standard T8	High-Output T8
1-lamp	58	80
2-lamp	112	160
3-lamp	170	240
4-lamp	224	320
6-lamp	336	480

T8 U-Lamps

Fixture	
1-lamp	32
2-lamp	60
3-lamp	92

4-foot T8 Lamps

Fixture	Standard T8	Highbay T8 HP ballast	Fixture	Standard T8	Highbay T8 HP ballast
1-lamp	31	38	5-lamp	143	184
2-lamp	58	74	6-lamp	174	220
3-lamp	85	110	8-lamp	232	288
4-lamp	112	144			

T12 Retrofit Baseline Wattage Figures

These wattages only apply for T12 lamps when the final product is an LED fixture, LED retrofit kit, or replacement LED lamps. Verification of existing T12's may be requested by DTE prior to reservation.

8-foot T12 Lamps		
Fixture	Standard T12	High-Output T12
1-lamp	75	112
2-lamp	123	207
3-lamp	210	319
4-lamp	246	414
6-lamp	369	621

T12 U-Lamps	
Fixture	
1-lamp	43
2-lamp	72
3-lamp	115

4-foot T12 Lamps			
Fixture	Standard T12	Fixture	Standard T12
1-lamp	43	5-lamp	187
2-lamp	72	6-lamp	216
3-lamp	115	8-lamp	288
4-lamp	144		

Contact Us

phone: **866.796.0512** (option 3)
email: **saveenergy@dteenergy.com**

web: **dteenergy.com/savenow**
fax: **313.664.1950**